

## ARP Odyssey 2800 Slider Locations and Values

Panel Description	Board	Location On Board	Value	Knob Color
PORTAMENTO	A-1	P2	1M AUD (LOG)	Black
VCO-1 - FREQUENCY - COURSE	B-1	P1	100K LINEAR	Blue
VCO-1 - FREQUENCY - FINE	B-1	P2	100K LINEAR	Blue
VCO-2 - FREQUENCY - COURSE	B-1	P3	100K LINEAR	Green
VCO-2 - FREQUENCY - FINE	B-1	P4	100K LINEAR	Green
LFO FREQ	B-1	P5	100K AUD (LOG)	Pink
VCO-1 (FM) - LFO	B-1	P6	100K AUD (LOG)	Pink
VCO-1 (FM) - SH/ADSR	B-1	P7	100K AUD (LOG)	Yellow
VCO-1 (PULSE WIDTH) - WIDTH	B-1	P8	100K LINEAR	Blue
VCO-1 (PULSE WIDTH) - MOD	B-1	P9	100K LINEAR	Pink
VCO-2 (FM) - LFO/SH MIXER OR PEDAL	B-1	P10	100K AUD (LOG)	Pink
VCO-2 (FM) - SH/ADSR	B-1	P11	100K AUD (LOG)	Yellow
VCO-2 (PULSE WIDTH) - WIDTH	B-1	P12	100K LINEAR	Green
VCO-2 (PULSE WIDTH) - MOD	B-1	P13	100K LINEAR	Pink
S/H MIXER - VCO-1	B-1	P14	100K LINEAR	Blue
S/H MIXER - NOISE GEN/VCO-2	B-1	P15	100K LINEAR	White
SAMPLE/HOLD - OUTPUT LAG	B-1	P16	1M AUD (LOG)	Yellow
VCF FREQ	C-1	P1	100K LINEAR	Black
VCF RESONANCE	C-1	P2	100K LINEAR	Black
HPF CUTOFF FREQ	C-1	P3	1M AUD (LOG)	Black
VCA GAIN	C-1	P4	100K LINEAR	Black
AR - ATTACK	C-1	P5	1M AUD (LOG)	Red
AR - RELEASE	C-1	P6	1M AUD (LOG)	Red
AUDIO MIXER - NOISE/RING MOD	C-1	P7	100K AUD (LOG)	White
AUDIO MIXER - VCO-1	C-1	P8	100K AUD (LOG)	Blue
AUDIO MIXER - VCO-2	C-1	P9	100K AUD (LOG)	Green
VCF - KYBD CV/SH MIXER OR PEDAL	C-1	P10	100K LINEAR	Black
VCF - SH/LFO	C-1	P11	100K LINEAR	Yellow
VCF - ADSR/AR	C-1	P12	100K LINEAR	Red
VCA - AR/ADSR	C-1	P13	100K AUD (LOG)	Red
ADSR - ATTACK	C-1	P14	1M AUD (LOG)	Red
ADSR - DECAY	C-1	P15	1M AUD (LOG)	Red
ADSR - SUSTAIN	C-1	P16	100K LINEAR	Red
ADSR - RELEASE	C-1	P17	1M AUD (LOG)	Red

Errors and omissions accepted. Information subject to change.

© 2013 Synth Patchers . All Rights Reserved. Synth Patchers is a SanPareil International Company.

[www.synthpatchers.com](http://www.synthpatchers.com)