

ARP Axse Slider Locations and Values

Panel Description	Board	Location On Board	Value	Knob Color
PORTAMENTO	Main Board	R26	1M AUD (LOG)	Black
VCO - LFO SINE	Main Board	R79	100K AUD (LOG)	Pink
VCO- LFO SQUARE	Main Board	R78	100K AUD (LOG)	Pink
VCO - S/H	Main Board	R77	100K AUD (LOG)	Yellow
VCO - ADSR	Main Board	R94	100K AUD (LOG)	Red
PULSE WIDTH	Main Board	R107	100K LINEAR	Blue
PULSE (WIDTH MOD) - LFO	Main Board	R105	100K AUD (LOG)	Pink
PULSE (WIDTH MOD) - ADSR	Main Board	R106	100K AUD (LOG)	Red
LFO FREQ	Main Board	R18	100K AUD (LOG)	Pink
AUDIO MIXER - NOISE	Main Board	R119	100K AUD (LOG)	White
AUDIO MIXER - VCO SAW	Main Board	R120	100K AUD (LOG)	Green
AUDIO MIXER - VCO SQUARE	Main Board	R121	100K AUD (LOG)	Blue
VCF - VCF FREQ	Main Board	R157	100K LINEAR	Black
VCF - RESONANCE	Main Board	R144	100K LINEAR	Black
VCF - KYBD CV S/H PEDAL	Main Board	R159	100K AUD (LOG)	Yellow
VCF - LFO	Main Board	R161	100K LINEAR	Pink
VCF - ADSR	Main Board	R160	100K LINEAR	Red
VCA - VCA GAIN	Main Board	R173	1M AUD (LOG)	Black
VCA - ADSR	Main Board	R170	1M AUD (LOG)	Red
ADSR - ATTACK	Main Board	R50	1M AUD (LOG)	Red
ADSR - DECAY	Main Board	R49	1M AUD (LOG)	Red
ADSR - SUSTAIN	Main Board	R45	100K LINEAR	Red
ADSR - RELEASE	Main Board	R54	1M AUD (LOG)	Red

Errors and omissions accepted. Information subject to change.

© 2013 Synth Patchers . All Rights Reserved. Synth Patchers is a SanPareil International Company.

www.synthpatchers.com